

533113US01

(G523US)

**TESTING DEVICE OF SEMICONDUCTOR INTEGRATED CIRCUIT
AND TEST METHOD THEREFOR**

Background of the Invention

Field of the Invention

The present invention relates to a testing device of a semiconductor integrated circuit that specifically includes more than one different logics, such as a memory core, and incorporates a JTAG circuit (circuit conforming to the Joint Test Action Group standard), and a method of testing the same.

Background Art

Fig. 9 is a block diagram illustrating the conventional testing device of a semiconductor integrated circuit that incorporates the JTAG circuit. The semiconductor integrated circuit mounted on the same chip includes two different logics (logic 1 and logic 2), and the logics each include the JTAG circuits each.

In the figure, reference numeral 11 is integrated into the logic 1, and denotes a Boundary Scan Register (hereunder, referred to as BSR) that composes a major part of the JTAG circuit, which has an equivalent function to the conventional test probe, and stores the test result of the logic 1. Reference numeral 12 denotes a Data Register

(hereunder, referred to as DR) in the JTAG circuit, and reference numeral 13 a Bypass Register (hereunder, referred to as BR), which bypasses the test data input to the output, thus forming the shortest route.

Reference numeral 14 denotes an Instruction Register (hereunder, referred to as IR), which reads and decodes the command bits from the well-known TAP (Test Access Port) controller not illustrated.

Reference numeral 15 denotes a selector connected to the foregoing registers each, which is selected and controlled by the IR 14 to send out either one of the register outputs. Reference numeral 21 denotes a BSR integrated into the logic 2, 22 a DR, 23 a BR, 24 an IR, and 25 a selector, and any of them has the same configuration as that of the logic 1.

Here, TDI signifies a test data input signal to the JTAG circuit, and TDO a test data output signal from the JTAG circuit, and the output from the selector 15 of the logic 1 is the input signal to the logic 2.

The operation of testing each of the logics twice and reading the test results in this configuration will be described with reference to a flow chart shown in Fig. 10.

First, in Step S1 the test mode of the logic 1 is set. Next, in Step S2 the first test of the logic 1 is executed, and in Step S3 the test result in the BSR 11 is

stored. Then, in Step S4 the test result of the first test stored in the BSR 11 is read out. This readout signal is inputted to the logic 2 by way of the selector 15, and outputted to the test data output TDO by way of the BR 23 and the selector 25 of the logic 2. Here, the selector 15 of the logic 1 is set to select the test result of the BSR 11 by the IR 14; and in the logic 2, the selector 25 is set to select the BR 23 by the IR 24.

And then, in Step S5 the second test of the logic 1 is executed, and in Step S6 the test result in the BSR 11 is stored.

In Step S7, the test result of the second test is read, and in the same manner as the first test, the test result signal from the BSR 11 is outputted to the TDO of the logic 2.

Next, in Step S8 the test mode of the logic 2 is set, and in Step S9, the first test of the logic 2 is carried out. In Step S10 the test result in the BSR 21 is stored, and in Step S11, the test result is read out.

The readout signal is outputted from the BSR 21 to the TDO by way of the selector 25.

Also in this case, the selector 25 is set to select the test result of the BSR 21 by the IR 24. And then, in Step S12 the second test of the logic 2 is carried out, and in Step 13 the test result in the BSR 21 is stored.

Next, in Step S14 the test result of the BSR 21 is read out. The readout signal is outputted to the TDO by way of the selector 25, in the same manner as the first test, and the test is completed in Step S15.

The conventional in-circuit test of a semiconductor integrated circuit by the JTAG circuit is carried out as above. And, in case of the two logics 1, 2 as the testing objects being simultaneously in the test, when the test result is read from the BSR 11 in one logic, for example, in the logic 1, the BR 23 in the logic 2 is made to function. However, the BR 23 or BR 13 is made to be valid, when the IR 24 or IR 14 of the JTAG circuit is all "1". Therefore, the logic that set the BR 23 or BR 13 has to slip out of the test mode (for example, RUNBIST) set by the IR 24 or IR 14, whereby the simultaneous testing of the logics accompanied with plural times readouts of the test results becomes impossible, which is disadvantageous.

Summary of the Invention

The present invention has been made in view of the above circumstances, and an object of the invention is to provide a testing device and a test method that attains the bypassing function being not influenced by the state of the Instruction Register.

According to one aspect of the present invention,

there is provided a testing device of a semiconductor integrated circuit having more than one different logics and JTAG circuits built in, which executes an in-circuit test of the logics. The JTAG circuit includes a boundary scan register that executes a test of the logic in accordance with a test data input and stores a test result; a data register; a pseudo bypass register having a bypassing function of the test data input; a first selector connected to the data register and the pseudo bypass register, which selectively takes out outputs of the registers; a bypass register having a bypassing function of the test data input; an instruction register for giving an operation command; and a second selector that is connected to the boundary scan register, the first selector, the bypass register, and the instruction register, which is selectively controlled by the instruction register. The JTAG circuits are provided to each of the logics, and the output from the second selector of a specific logic is an input of another logic.

According to another aspect of the present invention, there is provided a testing device of a semiconductor integrated circuit having more than one different logics and JTAG circuits built in, which executes an in-circuit test of the logics. Each of the logics is provided with: a control block including a boundary scan register that

executes a test of the logic in accordance with a test data input and stores a test result, a data register, a pseudo bypass register having a bypassing function of the test data input, and a first selector connected to each of the registers, which selectively takes out outputs of the registers; and a bypass register; an instruction register; and a second selector that is connected to these registers and the first selector, which is selectively controlled by the instruction register. The output from the second selector of a specific logic is an input of another logic.

According to another aspect of the present invention, there is provided a testing device of a semiconductor integrated circuit having more than one different logics and JTAG circuits built in, which executes an in-circuit test of the logics. Each of the logics is provided with: a control block including a boundary scan register that executes a test of the logic in accordance with a test data input and stores a test result, a data register, a pseudo bypass register having a bypassing function of the test data input, and a first selector connected to each of the registers, which selectively takes out outputs of the registers; a bypass register and an instruction register that are common to each of the control blocks; and a second selector connected to the each control block, the bypass register and the instruction register, which is selectively

controlled by the instruction register. The output from the first selector of a specific control block is an input of another control block.

According to another aspect of the present invention, there is provided a test method of a semiconductor integrated circuit, which carries out an in-circuit test thereof by a testing device thereof described above.

The testing device and test method of a semiconductor integrated circuit relating to the invention provides each of the logics with the JTAG circuit including: the BSR that executes a test of the logic in accordance with a test data input and stores a test result, the DR, the TR having a bypassing function of the test data input, the first selector connected to the DR and TR, which selectively takes out the outputs of the registers, a BR having a bypassing function of the test data input, the IR for giving an operation command, and the second selector that is connected to the BSR, the first selector, the BR, and the IR, which is selectively controlled by the IR, in which the output from the second selector of a specific logic is connected to the input of another logic, whereby, the bypassing function can be implemented which is not influenced by the state of the IR.

Further, it is possible to carry out the test without setting the test mode repeatedly after using the

bypassing function, thus leading to simplification of the test flow and accordingly a simultaneous testing of plural logics accompanied with plural times readouts of the test results becomes possible, and whereby the time for testing can be shortened.

Also, the testing device and test method of a semiconductor integrated circuit relating to the invention includes a selector on the input of the TR, whereby the test data input to be bypassed and arbitrary information can be inputted selectively. Information unique to the logic, for example, a pass or fail signal of the memory core can be added, and the information unique to the memory core can be read out at the same time of reading the output from the BSR.

Further, to configure the TR with plural bits will attain N-fold information.

Further, in the testing device and test method of a semiconductor integrated circuit relating to the invention, each of the logics is provided with: a control block including the BSR that executes a test of the logic in accordance with a test data input and stores a test result, the DR, the TR having a bypassing function of the test data input, and the first selector connected to each of the registers, which selectively takes out outputs of the registers; the BR; the IR that are common to each of the

control blocks; and the second selector connected to each control block, the BR and IR, which is selectively controlled by the IR, in which the output from the first selector of a specific control block is the input of another control block, whereby the JTAG circuit is configured. Thus, one JTAG circuit will be able to carry out a simultaneous testing of plural logics.

Other and further objects, features and advantages of the invention will appear more fully from the following description.

Brief Description of the Drawings

Fig. 1 is a block diagram of the first embodiment.

Fig. 2 is a flow chart of the first embodiment.

Fig. 3 is a block diagram illustrating the configuration of the TR and that constitute the major part of the second embodiment, and the signal paths to these components.

Figs. 4A to 4F are waveforms in correspondence with the mode transition of the TAP controller to illustrate the third embodiment..

Fig. 5 is a block diagram illustrating the configuration of the TR that constitute the major part of the third embodiment, and the signal paths to these components.

Figs. 6A to 6H are waveforms in correspondence with the mode transition of the TAP controller to illustrate the third embodiment.

Fig. 7 is a block diagram to illustrate the configuration of the fourth embodiment.

Fig. 8 is a block diagram to illustrate the configuration of the fourth embodiment.

Fig. 9 is a block diagram illustrating the conventional testing device of a semiconductor integrated circuit that incorporates the JTAG circuit.

Fig. 10 is a flow chart of the related art.

Detailed Description of the Preferred Embodiments

First Embodiment

The first embodiment of the invention will now be described with reference to the drawings.

Fig. 1 is a block diagram of the first embodiment, in which the same or the equivalent parts to Fig. 9 are given the same symbols to omit the explanations. The difference from Fig. 9 lies in that the first embodiment includes Transfer Registers in replacement of the BR 13 and 23, and the DR 12 and 22 controls the TR 16 and 26. In Fig. 1, 16 signifies a transfer register (TR) that constitutes the JTAG circuit of the logic 1, which assumes the same configuration as the BR 13, and has the

function to bypass the test data input signal TD1 to the output.

Reference numeral 17 signifies a first selector that is connected to the TR 16 and the DR 12, which is selectively controlled and selected by the DR 12.

Also, 18 signifies a second selector that is connected to the BSR 11, the output terminal of the first selector 17, the BR 13, and the IR 14, which is, in the same manner as in Fig. 9, selectively controlled by the IR 14, and the output of the second selector is the input signal to the logic 2.

Further, 26 signifies the TR, 27 a first selector, 28 a second selector incorporated into the logic 2; and these are configured in the same manner as those in the logic 1, and the output of the second selector 28 is the test data output signal TDO.

With this configuration, the operation of testing each of the logics twice and reading the test result will be described with reference to the flow chart shown in Fig. 2.

First, in Step S21 the test modes of the logic 1 and the logic 2 are set. Next, in Step S22 the first tests of the logic 1 and the logic 2 are executed, and in Step S23 each test results are stored into the BSR 11 and the BSR 21. Then, in Step S24 the first test result in the logic 1 is

read out, which is stored in the BSR 11. This readout signal is inputted to the logic 2 by way of the second selector 18 that is selecting the BSR 11, according to the IR 14.

In the logic 2, the DR 22 makes the first selector 27 select the TR 26, and the IR 24 makes the second selector 28 select the output from the first selector 27. Therefore, the test result signal from the logic 1 is outputted to the test data output TDO by way of the TR 26, the first selector 27, and the second selector 28 of the logic 2.

And then, in Step S25 the first test result of the logic 2 is read, which is stored in the BSR 21. At this moment, since the second selector 28 is selecting the BSR 21 according to the IR 24 in the logic 2, the readout signal is outputted to the test data output TDO by way of the second selector 28.

Thereafter, in Step S26 the second tests of the logic 1 and the logic 2 are carried out, and in Step S27 each test results are stored into the BSR 11 and the BSR 21. Then, in Step S28 the second test result of the logic 1 is read out, and the test result signal from the BSR 11 is outputted to the TDO of the logic 2 by way of the same route as that of the first test.

Also, in Step S29 the second test result of the

logic 2 is read out, and the test result signal from the BSR 21 is outputted to the TDO by way of the same route as that of the first test, and in Step S30 the test is completed.

Thus, in this embodiment, since the DR 12 and 22 controls to select the TR 16 and 26, respectively, it is possible to achieve the bypassing function that is not influenced by the state of the IR 14, or the IR 24.

Further, in the conventional testing device as shown in Fig. 9, since the IR 14 and 24 selectively controls the BR 13 and 23, at the reading of the test result of the logic 1, when carrying out the test of the logic 2 after bringing the BR 23 of the logic 2 into function, it has been necessary to set the test mode repeatedly, as shown in the Step S8 in Fig. 10. However, since this embodiment utilizes the bypassing function of the TR 16 and 26, the logic 2 will not slip out of the test mode, thus leading to simplification of the test flow.

Therefore, as shown in the flow chart in Fig. 2, a simultaneous testing of plural logics accompanied with plural times readouts of the test results becomes possible, and the time for testing can be shortened.

Second Embodiment

Now, the second embodiment of the invention will be

explained with reference to the drawings.

Fig. 3 is a block diagram illustrating the configuration of the TR 16 and 26 that constitute the major part of the second embodiment, and the signal paths to these components.

In Fig. 3, 16, 26 denote the TR 16 of the logic 1, and the TR 26 of the logic 2, respectively. Reference numeral 30 denotes the third selector provided on the input of the TR 16 or the TR 26, and a Pass-Data being one input of the third selector 30 is directly connected to the test data input TDI in Fig. 1, to which the test data to be bypassed is inputted. An IN-Data being the other input is an input terminal to receive arbitrary information in each of the logics, such as, a pass or fail signal of the memory core. These input are selectively controlled and selected by a SHIFT DR signal of the TAP controller not illustrated. That is, the information unique to each of the logics can be added to the TR 16 and 26 by way of the IN-Data.

Fig. 4 illustrates waveforms in correspondence with the mode transition of the TAP controller. As shown in Fig. 4B, the input of the SHIFT-DR signal makes the third selector 30 in Fig. 3 select the IN-Data; accordingly, the information of the IN-Data as shown in Fig. 4E appears at the TDO as shown in Fig. 4F, which can be read out together with the Pass-Data being the test data input.

Third Embodiment

Next, the third embodiment of the invention will be described with reference to the drawings.

Fig. 5 is a block diagram illustrating the configuration of the TR 16 and 26 that constitute the major part of the third embodiment, and the signal paths to these components.

Here, in Fig. 5, the symbols of the TR are illustrated in correspondence with the logic 1 as an example. That is, in Fig. 5, 16(1), 16(2), . . . 16(N) each denote the TR of plural bits, and 30(1), 30(2), . . . 30(N) denote the third selectors provided on the inputs of the TR 16(1), TR 16(2), ... TR 16(N). The functions and input signals of the selectors, and so forth are equivalent to those of the third selector 30 in the second embodiment.

Fig. 6 illustrates, in the same manner as Fig. 4, waveforms in correspondence with the mode transition of the TAP controller, and plural arbitrary information as shown in Fig. 6E through Fig. 6G are prepared as the IN-Data. As shown in Fig. 6B, the input of the SHIFT-DR signal makes the third selectors 30(1), 30(2), . . . 30(N) of each bit in Fig. 5 sequentially select the IN-Data; accordingly, the information of the IN-Data as shown in Fig. 6E through Fig. 6G appear sequentially at the TDO as shown in Fig. 6H,

which can be read out together with the Pass-Data being the test data input.

This embodiment is designed to be able to add arbitrary information inherent to each of the logics by each bit as mentioned above, and it is accordingly possible to attain N-fold information, as compared to the second embodiment.

Fourth Embodiment

Next, the fourth embodiment of the invention will be described with reference to the drawings.

Fig. 7 and Fig. 8 illustrate the configuration of the fourth embodiment. In these figures, the same or the equivalent parts to Fig. 1 are given the same symbols to omit the explanations.

In Fig. 7, B1 signifies a first control block of logic 1 including the BSR 11, TR 16, DR 12, and a first selector 37 that is connected to these registers and controlled by the DR 12. Reference numeral 38 signifies a second selector that is connected to the first selector 37, BR 13, and IR 14, and is selectively controlled by the IR 14. B2 signifies a second control block of logic 2 including the BSR 21, TR 26, DR 22, and a first selector 47 that is connected to these registers and controlled by the DR 22. Reference numeral 48 signifies a second selector

that is connected to the first selector 47, BR 23, and IR 24, and is selectively controlled by the IR 24.

This embodiment provides the logic 1, logic 2 with the control blocks B1 and B2, respectively, to thereby separate the JTAG circuit from the logics. This configuration realizes a circuit configuration, for example, as shown in Fig. 8. In this Fig. 8, JC is a JTAG circuit that includes a control block B, a BSR 33, an IR 34, and a selector 58 that is connected to these and controlled by the IR 34. Further, the control block B includes, as the arrow shows the detailed construction, the control block B1 corresponding to the logic 1 and the control block B2 corresponding to the logic 2.

Thus, the BR 33 and the IR 34 and the selector 58 function as the common components to both the blocks B1, B2.

With this configuration, one JTAG circuit will implement a simultaneous testing of plural logics.

Obviously many modifications and variations of the present invention are possible in the light of the above teachings. It is therefore to be understood that within the scope of the appended claims the invention may be practiced otherwise than as specifically described.

The entire disclosure of a Japanese Patent Application No. 2001-224899, filed on July 25, 2001 including specification, claims, drawings and summary, on

1870
 1871
 1872
 1873
 1874
 1875
 1876
 1877
 1878
 1879
 1880
 1881
 1882
 1883
 1884
 1885
 1886
 1887
 1888
 1889
 1890
 1891
 1892
 1893
 1894
 1895
 1896
 1897
 1898
 1899
 1900
 1901
 1902
 1903
 1904
 1905
 1906
 1907
 1908
 1909
 1910
 1911
 1912
 1913
 1914
 1915
 1916
 1917
 1918
 1919
 1920
 1921
 1922
 1923
 1924
 1925
 1926
 1927
 1928
 1929
 1930
 1931
 1932
 1933
 1934
 1935
 1936
 1937
 1938
 1939
 1940
 1941
 1942
 1943
 1944
 1945
 1946
 1947
 1948
 1949
 1950
 1951
 1952
 1953
 1954
 1955
 1956
 1957
 1958
 1959
 1960
 1961
 1962
 1963
 1964
 1965
 1966
 1967
 1968
 1969
 1970
 1971
 1972
 1973
 1974
 1975
 1976
 1977
 1978
 1979
 1980
 1981
 1982
 1983
 1984
 1985
 1986
 1987
 1988
 1989
 1990
 1991
 1992
 1993
 1994
 1995
 1996
 1997
 1998
 1999
 2000
 2001
 2002
 2003
 2004
 2005
 2006
 2007
 2008
 2009
 2010
 2011
 2012
 2013
 2014
 2015
 2016
 2017
 2018
 2019
 2020
 2021
 2022
 2023
 2024
 2025
 2026
 2027
 2028
 2029
 2030
 2031
 2032
 2033
 2034
 2035
 2036
 2037
 2038
 2039
 2040
 2041
 2042
 2043
 2044
 2045
 2046
 2047
 2048
 2049
 2050
 2051
 2052
 2053
 2054
 2055
 2056
 2057
 2058
 2059
 2060
 2061
 2062
 2063
 2064
 2065
 2066
 2067
 2068
 2069
 2070
 2071
 2072
 2073
 2074
 2075
 2076
 2077
 2078
 2079
 2080
 2081
 2082
 2083
 2084
 2085
 2086
 2087
 2088
 2089
 2090
 2091
 2092
 2093
 2094
 2095
 2096
 2097
 2098
 2099
 2100
 2101
 2102
 2103
 2104
 2105
 2106
 2107
 2108
 2109
 2110
 2111
 2112
 2113
 2114
 2115
 2116
 2117
 2118
 2119
 2120
 2121
 2122
 2123
 2124
 2125
 2126
 2127
 2128
 2129
 2130
 2131
 2132
 2133
 2134
 2135
 2136
 2137
 2138
 2139
 2140
 2141
 2142
 2143
 2144
 2145
 2146
 2147
 2148
 2149
 2150
 2151
 2152
 2153
 2154
 2155
 2156
 2157
 2158
 2159
 2160
 2161
 2162
 2163
 2164
 2165
 2166
 2167
 2168
 2169
 2170
 2171
 2172
 2173
 2174
 2175
 2176
 2177
 2178
 2179
 2180
 2181
 2182
 2183
 2184
 2185
 2186
 2187
 2188
 2189
 2190
 2191
 2192
 2193
 2194
 2195
 2196
 2197
 2198
 2199
 2200
 2201
 2202
 2203
 2204
 2205
 2206
 2207
 2208
 2209
 2210
 2211
 2212
 2213
 2214
 2215
 2216
 2217
 2218
 2219
 2220
 2221
 2222
 2223
 2224
 2225
 2226
 2227
 2228
 2229
 2230
 2231
 2232
 2233
 2234
 2235
 2236
 2237
 2238
 2239
 2240
 2241
 2242
 2243
 2244
 2245
 2246
 2247
 2248
 2249
 2250
 2251
 2252
 2253
 2254
 2255
 2256
 2257
 2258
 2259
 2260
 2261
 2262
 2263
 2264
 2265
 2266
 2267
 2268
 2269
 2270
 2271
 2272
 2273
 2274
 2275
 2276
 2277
 2278
 2279
 2280
 2281
 2282
 2283
 2284
 2285
 2286
 2287
 2288
 2289
 2290
 2291
 2292
 2293
 2294
 2295
 2296
 2297
 2298
 2299
 2300
 2301
 2302
 2303
 2304
 2305
 2306
 2307
 2308
 2309
 2310
 2311
 2312
 2313
 2314
 2315
 2316
 2317
 2318
 2319
 2320
 2321
 2322
 2323
 2324